

## AMENDMENTS TO THE CLAIMS

This listing of claims will replace all prior versions, and listing, of claims in the application.

1. (Currently Amended) A signal filtering mechanism, comprising:
  - a Kalman filter capable of receiving an input signal, a measured quantity signal, and a variance estimate signal for the measured quantity signal, and outputting a state estimate signal; and
  - a variance estimator capable of estimating the variance of the measured quantity signal and generating the variance estimate signal for use in filtering the input signal and the measured quantity signal, wherein estimating the variance of the measured quantity signal includes determining a smoothed estimate of the measured quantity's final variance from the measured quantity signal.
2. (Original) The signal filtering mechanism of claim 1, wherein determining the smoothed estimate comprises:
  - determining the squared instantaneous prediction error of the measured quantity signal;
  - smoothing the determined, squared instantaneous prediction error; and
  - estimating the measured quantity's variance from the smoothed squared instantaneous prediction error.
3. (Original) The signal filtering mechanism of claim 1, wherein determining the smoothed estimate comprises:
  - determining the absolute instantaneous prediction error in the measured quantity signal;
  - smoothing the determined, absolute instantaneous prediction error; and
  - estimating the measured quantity's variance from the smoothed absolute instantaneous prediction error.
4. (Original) A method for estimating the variance of a measured quantity used to predict the current state of a discrete, vector-state, scalar-measurement system, the method comprising:
  - estimating the variance of a measured quantity for use in filtering an input quantity and the measured quantity;

determining a smoothed estimate of an instantaneous prediction error's variance; and  
filtering the input quantity and the measured quantity through a Kalman filter using the  
estimated input variance of the measured quantity signal.

5. (Original) The method of claim 4, wherein determining the smoothed estimate of the  
variance of the instantaneous prediction error of the measured quantity signal comprises:

determining the squared instantaneous prediction error in the measured quantity signal;  
smoothing the determined, squared instantaneous prediction error; and  
estimating the variance from the smoothed squared instantaneous prediction error.

6. (Original) The method of claim 5, further comprising initializing a plurality of quantities  
used in estimating the current state of the discrete, vector-state, scalar-measurement system.

7. (Original) The method of claim 6, wherein initializing the plurality of quantities includes:  
setting the prediction of the initial state of the system to a first predetermined value; and  
setting the initial prediction covariance matrix associated with the predicted initial state  
of the system to a second predetermined value; and  
one of:

setting the error filter gain to a third predetermined value; or  
setting the smoothed squared instantaneous prediction error to 0.

8. (Original) The method of claim 7, wherein the third predetermined value is a vector of  
ones.

9. (Original) The method of claim 7, wherein the error filter gain is set to a third  
predetermined value and filtering the input quantity and the measured quantity includes  
determining a Kalman filter gain vector, a current state vector estimate, and a state vector  
estimate covariance matrix after estimating the variance of the measured quantity.

10. (Original) The method of claim 7, wherein the smoothed squared instantaneous  
prediction error is set to 0 and filtering the input quantity and the measured quantity includes  
determining a Kalman filter gain vector, a current state vector estimate, and a state vector  
estimate covariance matrix before estimating the variance.

1 11. (Original) The method of claim 4, wherein determining the smoothed estimate of the  
2 variance of the instantaneous prediction error of the measured quantity signal comprises:

3 determining the absolute instantaneous prediction error in the measured quantity signal;  
4 smoothing the determined, absolute instantaneous prediction error; and  
5 estimating the variance from the smoothed absolute instantaneous prediction error.

1 12. (Original) The method of claim 11, further comprising initializing a plurality of quantities  
2 used in estimating the current state of the discrete, vector-state, scalar-measurement system.

1 13. (Original) The method of claim 12, wherein initializing the plurality of quantities  
2 includes:

3 setting the prediction of the initial state of the system to a first predetermined value; and  
4 setting the initial prediction covariance matrix associated with the predicted initial state  
5 of the system to a second predetermined value; and  
6 one of:

7 setting the error filter gain to a third predetermined value; or  
8 setting the smoothed absolute instantaneous prediction error to 0.

1 14. (Original) The method of claim 13, wherein the third predetermined value is a vector of  
2 ones.

1 15. (Original) The method of claim 13, wherein the error filter gain is set to a third  
2 predetermined value and filtering the input quantity and the measured quantity includes  
3 determining a Kalman filter gain vector, a current state vector estimate, and a state vector  
4 estimate covariance matrix after estimating the variance of the measured quantity.

1 16. (Original) The method of claim 13, wherein the smoothed absolute instantaneous  
2 prediction error is set to 0 and filtering the input quantity and the measured quantity includes  
3 determining a Kalman filter gain vector, a current state vector estimate, and a state vector  
4 estimate covariance matrix before estimating the variance.

1 17. (Currently Amended) A method for estimating the current state of a discrete, vector-state,  
2 scalar-measurement system, the method comprising:

3 determining a current state vector prediction from a previous state vector estimate and an  
4 input vector;  
5 determining a current state vector prediction covariance matrix associated with the  
6 current state vector prediction from a previous state vector covariance matrix  
7 associated with the previous state vector estimate;  
8 estimating the variance of a measured quantity, wherein estimating the variance includes:  
9 determining a squared instantaneous prediction error of the measured quantity  
10 from the measured quantity and one of the current state vector estimate  
11 and the previous state vector estimate;  
12 smoothing the squared instantaneous prediction error; and  
13 estimating the final variance of the measured quantity from the smoothed squared  
14 instantaneous prediction error;  
15 determining a current Kalman filter gain vector from the current state vector prediction  
16 covariance matrix and the measured quantity variance estimate;  
17 determining a current state vector estimate from the Kalman filter gain, the current state  
18 vector prediction, and the measured quantity;  
19 determining the current state vector covariance matrix associated with the current state  
20 vector estimate from the Kalman filter gain and the current state vector prediction  
21 covariance matrix; and  
22 iterating the above.

1 18. (Original) The method of claim 17, further comprising initializing a plurality of quantities  
2 used in estimating the current state of the discrete, vector-state, scalar-measurement system.

1 19. (Original) The method of claim 18, wherein initializing the plurality of quantities  
2 includes:

3 setting the value of the current state vector prediction to a first predetermined value;  
4 setting the current state vector prediction covariance matrix to a second predetermined  
5 value; and  
6 performing one of:  
7 setting an error filter gain to a third predetermined value; or  
8 setting the squared instantaneous prediction error to 0.

1 20. (Original) The method of claim 17, wherein the current state vector estimate, the current  
2 state vector prediction covariance matrix, and the current Kalman filter gain are updated after the  
3 variance of the measured quantity is estimated.

1 21. (Original) The method of claim 20, wherein, in estimating the variance of the measured  
2 quantity includes:

3 determining the squared instantaneous prediction error in the measured quantity includes  
4 applying the following analysis:

$$e^2[n] = (z[n] - H[n] \hat{x}[n | n-1])^2;$$

6 smoothing the determined, squared instantaneous prediction error includes applying the  
7 following analysis:

$$\hat{\sigma}_e^2[n] = \hat{\sigma}_e^2[n-1] + H[n] G[n] (e^2[n] - \hat{\sigma}_e^2[n-1]); \text{ and}$$

9 estimating the variance of the measured quantity from the smoothed squared  
10 instantaneous prediction error comprises:

11 setting the estimated variance to a fourth predetermined value if the Kalman filter  
12 is not stable; or

13 applying the following analysis if the Kalman filter is stable:

14 determining the value of  $a[n]$  from:

$$a[n] = \frac{H[n] A[n] H[n]^T}{H[n] H[n]^T};$$

16 determining the value of  $q[n]$  from:

$$q[n] = (H[n] B[n]) Q[n] (H[n] B[n])^T; \text{ and}$$

18 solving for  $\hat{R}[n]$  from

$$\hat{R}[n]^2 (2a^2[n] - 1) + \hat{R}[n] [\hat{\sigma}_e^2[n] (1 - 3a^2[n]) - 2q[n]] + \hat{\sigma}_e^2[n] (q[n] + \hat{\sigma}_e^2[n] a^2[n]) = 0.$$

1 22. (Original) The method of claim 17, wherein the current state vector estimate, the current  
2 state vector prediction covariance matrix, and the current Kalman filter gain are updated before  
3 the variance of the measured quantity is estimated.

23. (Original) The method of claim 22, wherein, in estimating the variance of the measured quantity includes:

determining the squared instantaneous prediction error of the measured quantity includes applying the following analysis:

$$e^2[n] = (z[n] - H[n] \hat{x}[n])^2;$$

smoothing the determined, squared instantaneous prediction error includes applying the following analysis:

$$\hat{\sigma}_e^2[n] = \hat{\sigma}_e^2[n-1] + H[n] G[n] (e^2[n] - \hat{\sigma}_e^2[n-1]); \text{ and}$$

estimating the variance from the smoothed squared instantaneous prediction error comprises:

setting the estimated variance to a fourth predetermined value if the Kalman filter is not stable; or

applying the following analysis if the Kalman filter is stable:

determining the value of  $a[n]$  from:

$$a[n] = \frac{H[n] A[n] H[n]^T}{H[n] H[n]^T};$$

determining the value of  $q[n]$  from:

$$q[n] = (H[n] B[n]) Q[n] (H[n] B[n])^T; \text{ and}$$

solving for  $\hat{R}[n]$  from

$$\hat{R}[n]^4 \frac{a^2[n]}{(\hat{\sigma}_e^2[n])^2} + \hat{R}[n]^3 \frac{1 - 3a^2[n]}{\hat{\sigma}_e^2[n]} + \hat{R}[n]^2 (2a^2[n] - 1) \left( 1 - \frac{q[n]}{\hat{\sigma}_e^2[n]} \right) + (\hat{R}[n] 3q[n] + q^2[n]) (a^2[n] - 1) = 0.$$

24. (Original) A signal filtering mechanism, comprising:

means for receiving an input signal, a measured quantity signal, and a variance estimate signal for the measured quantity signal, and outputting a state estimate signal; and

means for estimating the variance of the measured quantity signal and generating the variance estimate signal for use in filtering the input signal and the measured

quantity signal, wherein estimating the variance of the measured quantity signal includes determining a smoothed estimate of the measured quantity's final variance from the measured quantity signal.

25. (Original) The signal filtering mechanism of claim 24, wherein determining the smoothed estimate comprises:

determining the squared instantaneous prediction error of the measured quantity signal;  
smoothing the determined, squared instantaneous prediction error; and  
estimating the measured quantity's variance from the smoothed squared instantaneous prediction error.

26. (Original) The signal filtering mechanism of claim 24, wherein determining the smoothed estimate comprises:

determining the absolute instantaneous prediction error in the measured quantity signal;  
smoothing the determined, absolute instantaneous prediction error; and  
estimating the measured quantity's variance from the smoothed absolute instantaneous prediction error.

27. (Currently Amended) A apparatus for estimating the variance of a measured quantity used to predict the current state of a discrete, vector-state, scalar-measurement system, the method comprising:

means for estimating the variance of a measured quantity for use in filtering an input quantity and the measured quantity;  
means for determining a smoothed estimate of an instantaneous prediction error's final variance; and  
means for filtering the input quantity and the measured quantity through a Kalman filter using the estimated input variance of the measured quantity signal.

28. (Original) The apparatus of claim 27, wherein the means for determining the smoothed estimate of the variance of the instantaneous prediction error of the measured quantity signal comprises:

means for determining the squared instantaneous prediction error in the measured quantity signal;

means for smoothing the determined, squared instantaneous prediction error; and  
means for estimating the variance from the smoothed squared instantaneous prediction error.

29. (Original) The apparatus of claim 27, wherein the means for determining the smoothed estimate of the variance of the instantaneous prediction error of the measured quantity signal comprises:

means for determining the absolute instantaneous prediction error in the measured quantity signal;

means for smoothing the determined, absolute instantaneous prediction error; and

means for estimating the variance from the smoothed absolute instantaneous prediction error.

30. (Currently Amended) A program storage medium encoded with instructions that, when executed by a computing apparatus, perform a method for estimating the variance of a measured quantity used to predict the current state of a discrete, vector-state, scalar-measurement system, the method comprising:

estimating the variance of a measured quantity for use in filtering an input quantity and the measured quantity;

determining a smoothed estimate of an instantaneous prediction error's final variance; and

filtering the input quantity and the measured quantity through a Kalman filter using the estimated input variance of the measured quantity signal.

31. (Currently Amended) The program storage medium of claim 30, wherein determining the smoothed estimate of the variance of the instantaneous prediction error of the measured quantity signal in the encoded method comprises:

determining the squared instantaneous prediction error in the measured quantity signal;

smoothing the determined, squared instantaneous prediction error; and

estimating the final variance from the smoothed squared instantaneous prediction error.



1 32. (Currently Amended) The program storage medium of claim 30, wherein determining the  
2 smoothed estimate of the variance of the instantaneous prediction error of the measured quantity  
3 signal in the encoded method comprises:

4 determining the absolute instantaneous prediction error in the measured quantity signal;  
5 smoothing the determined, absolute instantaneous prediction error; and  
6 estimating the final variance from the smoothed absolute instantaneous prediction error.

1 33. (Currently Amended) A computing apparatus programmed to perform a method for  
2 estimating the variance of a measured quantity used to predict the current state of a discrete,  
3 vector-state, scalar-measurement system, the method comprising:

4 estimating the variance of a measured quantity for use in filtering an input quantity and  
5 the measured quantity;  
6 determining a smoothed estimate of an instantaneous prediction error's final variance;  
7 and  
8 filtering the input quantity and the measured quantity through a Kalman filter using the  
9 estimated input variance of the measured quantity signal.

1 34. (Original) The computing apparatus of claim 33, wherein determining the smoothed  
2 estimate of the variance of the instantaneous prediction error of the measured quantity signal in  
3 the programmed method comprises:

4 determining the squared instantaneous prediction error in the measured quantity signal;  
5 smoothing the determined, squared instantaneous prediction error; and  
6 estimating the variance from the smoothed squared instantaneous prediction error.

1 35. (Original) The computing apparatus of claim 33, wherein determining the smoothed  
2 estimate of the variance of the instantaneous prediction error of the measured quantity signal in  
3 the programmed method comprises:

4 determining the absolute instantaneous prediction error in the measured quantity signal;  
5 smoothing the determined, absolute instantaneous prediction error; and  
6 estimating the variance from the smoothed absolute instantaneous prediction error.